

Sécurité Cam-Install Caméras Câblage Technologies

Tutoriel pour activer les notifications sur mouvements (DMSS)

Step by Step Instructions

1. Launch DMSS Mobile App. From the "Device" page, tap on the 3 dots next to the device you want to setup notifications on

12:13		LTE	2⊿ û
	Device		€
Q Search			00
😈 Live		Playbac	k
N43BU82 Lab			
Local Device			
— X72 Lab		۲	
Local Device			
— X82 Lab		۲	344
 Local Device 			
N54 Lab		۲	
Local Device			
- NVR6A08		۲	•••
Local Device			
- N42B2P		۲	
l o Local Device			
Device	Message	м	e
<			

2. Tap on "Device Details"

12:13		LTE 🔊 🖗
	Device	\oplus
Q Search		8
Uve) Playback
• N43BU82 L	ab	
Local Device		
X72 Lab		۰۰۰ (۱)
Local Device		
— X82 Lab		۰۰۰ 🛞
Local Device		
- N54 Lab		۰۰ ا
Device Det	ails	
Move to the	е Тор	
- N42B2P		• ••
O Local Device		
Device	Message	Me
\$	-	

3. Tap on "Multi-channel Alarm Subscription"

LTE 🖌 🕯

<	Device Deta	ails	
(Bernander)	N54 Lab Online		ß
	Device Model:un Device SN:68030	known IC9PAZF7253	
Alarm Settin	gs		
Multi-chann	el Alarm Subscriptior	1	
Turn on/off No message push	tification switch to contro and storage of phone.	all sub-channel's	2
 Devices bo messages these devi 	ound through local binding . Each time you close DMS ce will be lost.	cannot save alarm IS App, messages from	
Disable Alar	rm Linkage		
Turn on/off the the linked devi	: Disable Alarm Linkage sv ce's alarm	witch to control	0
Video Play S	ettings		
Stream Set	ting		3
General Con	fig		
UPnP 🔘			
Enable to impo videos.	ove transmission speed to	quickly display live	3
Third-party	DDNS 💿		
Configure to bi domain to the directly access	nd the third-party DDNS device Extranet IP to s the device.	Please config	3
Others			
<	-		

12:15

4. Enable the slider at the top right.

Tab on "Period Settings" if you want to adjust the times of the day you want to receive notifications.

Then tap on the type of alarm event you want to receive notifications for (Motion

Detection, Intrusion Alarm, etc.)

12:15

LTE 🔊 🛱

<

N54 Lab

Clear

N54 Lab



After enabling it, only alarms of the subscribed alarm types will be pushed

Period Settings	00:00-23:59	5
Motion Detection		3
SMD		2
Intrusion Alarm		2
Tripwire Alarm		3
Scene Changing		3
Cam Masking		ş
Disk Alarm		3
People Alarm		3
Temperature Not within Thresholds		2
Save		
< 👄		

5. Check the boxes next to all the camera channels you want to receive notifications from.

When you are done tap on the back arrow at the top left

12:16		LTE 🔬 🛱
<	Motion Detection	Select All
IPC		0
IPC		0
DH-SD6C34	25XB-HNR-A-PV1	0
IPC4		0
IPC		0
IPC2		0
IPC3		0
IPC4		0
IPC		0
IPC2		0
DB11 Irvine		
Fisheye		
N45EFN2		
<		

6. Verify that the number of channels you selected in the previous steps shows up next to the alarm type you selected.

Tap "Save" at the bottom

12:16		LTE 🔬 🛍
<	N54 Lab	Clear
N54 Lab		
After enabling it, will be pushed	only alarms of the sul	oscribed alarm types
Period Settings		00:00-23:59 >
Motion Detectio	n	10 >
SMD		2
Intrusion Alarm		3
Tripwire Alarm		ž
Scene Changing	Ĩ.	>
Cam Masking		>
Disk Alarm		2
People Alarm		2
Temperature No	t within Thresholds	2
	Save	
<		

Note: If you have completed all the steps above and still not able to receive notification, you might need to check

notification permission on your mobile phone.